



# TAI-SAW TECHNOLOGY CO., LTD.

No. 3, Industrial 2nd Rd., Ping-Chen Industrial District,  
Taoyuan, 324, Taiwan, R.O.C.

TEL: 886-3-4690038 FAX: 886-3-4697532

E-mail: [tstsales@mail.taisaw.com](mailto:tstsales@mail.taisaw.com) Web: [www.taisaw.com](http://www.taisaw.com)

## Approval Sheet For Product Specification

Issued Date: Sep, 15, 2008

Product Name: SAW Filter 1210 MHz SMD 3.0X3.0 mm

TST Parts No.: TA0888A

Customer Parts No.: \_\_\_\_\_


Company: \_\_\_\_\_

Division: \_\_\_\_\_

Approved by : \_\_\_\_\_

Date: \_\_\_\_\_

Checked by: \_\_\_\_\_ Bob Chau 

Approval by: \_\_\_\_\_ Francis Chen 

Date: \_\_\_\_\_ 9, 15, 2008



# TAI-SAW TECHNOLOGY CO., LTD.

No. 3, Industrial 2nd Rd., Ping-Chen Industrial District,

Taoyuan, 324, Taiwan, R.O.C.

TEL: 886-3-4690038 FAX: 886-3-4697532

E-mail: [tstsales@mail.taisaw.com](mailto:tstsales@mail.taisaw.com)

Web: [www.taisaw.com](http://www.taisaw.com)

## SAW Filter 1210 MHz

MODEL NO.:TA0888A

REV. NO.:1

### A. MAXIMUM RATING:

1. Input Power Level: 10 dBm
2. DC Voltage : 3V
3. Operating Temperature: -40°C to +85°C
4. Storage Temperature: -50°C to +95°C

RoHS Compliant  
Lead free  
Lead-free soldering

### B. ELECTRICAL CHARACTERISTICS:

Terminating source impedance (differential) :  $Z_s = 150 \ \Omega \ // \ 36 \text{ nH}$


Terminating load impedance (differential) :  $Z_L = 150 \ \Omega \ // \ 36 \text{ nH}$

| Item                                          | Unit | Min. | Typ. | Max. | Note |
|-----------------------------------------------|------|------|------|------|------|
| <b>Center Frequency</b> <b>Fc</b>             | MHz  | -    | 1210 | -    | -    |
| <b>Bandwidth at -2 dB</b>                     | MHz  | 60   | 77   | -    | -    |
| <b>Insertion Loss</b> in 1180~1240 MHz        | dB   | -    | 3.9  | 5    | -    |
| <b>Amplitude ripple</b> (1180 MHz ~ 1240 MHz) | dB   | -    | 1    | 2    | -    |
| <b>Phase error</b> (1180 MHz ~ 1240 MHz) (3)  | deg  | -    | 3    | 5    | -    |
| <b>I/O VSWR</b> (1180 MHz ~ 1240 MHz)         |      | -    | 1.6  | 2.5  | -    |
| <b>CMDR</b> (1180 MHz ~ 1240 MHz)             | dB   | 22   | 25   | -    | -    |
| <b>Attenuation</b> (1)                        |      |      |      |      |      |
| 50 ~ 1110 MHz                                 | dB   | 44   | 49   | -    | -    |
| 1320 ~ 3000 MHz                               | dB   | 36   | 38.5 | -    | -    |
| 3000 ~ 4250 MHz                               | dB   | 35   | 41   | -    | -    |
| 4000 ~ 6000 MHz                               | dB   | 30   | 37   | -    | -    |

#### Notes :

- (1) The amplitude reference is insertion loss at Fc.
- (2) The amplitude ripple is defined as the max. level – min. level over any 36 MHz block of the given bandwidth.
- (3) The phase error is measured over any 36 MHz block of the given bandwidth.


### C.OUTLINE DRAWING:




△ : Year Code (2006->6, ..., 2009->9)

□ : Date Code (Follow the table from planner each year)


### D. MEASUREMENT CIRCUIT:




E. PCB Footprint:




## F. Frequency Characteristics :






Reflection Functions :

S11




S22




## G. PACKING:

### 1. REEL DIMENSION

(Reel Count : 7''=1000 ; 13''=3000 )



### 2.TAPE DIMENSION



**H. RECOMMENDED REFLOW PROFILE :**

