



5300 Beethoven Street, Los Angeles, CA 90066  
 TEL: (310)306-5556 • FAX: (310)577-9887  
 WEB: [www.ophirrf.com](http://www.ophirrf.com) • E-MAIL: [sales@ophirrf.com](mailto:sales@ophirrf.com)

## Solid State Broadband High Power RF Amplifier

The 5055 is a 25 Watt broadband amplifier that covers the 1.0 – 3.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 5055 comes with an extended multiyear

## MODEL 5055

1.0 - 3.0 GHz  
 25 WATTS

	Parameter	Specification @ 25° C
<b>Electrical</b>		
1	Frequency Range	1.0 – 3.0 GHz
2	Saturated Output Power	25 Watts typical
3	Power Output @ 1dB Comp.	20 Watts min
4	Small Signal Gain	+45 dB min
5	Small Signal Gain Flatness	± 2.0 dB max
6	IP <sub>3</sub>	+53 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 20 Watts
9	Spurious Signals	> -60 dBc typical @ 20 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	220 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
<b>Mechanical</b>		
16	Dimensions	19" x 3.5" x 18"
17	Weight	30 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<b>Environmental</b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

## CIRCUIT PROTECTIONS

◊ Thermal Overload

## ORDERING MODELS

- ◊ R - Rear Panel Connectors
- ◊ F - Front Panel Connectors
- ◊ RE - R model w/Control Option
- ◊ FE - F model w/Control Option
- ◊ RT - RE model w/Ethernet Interface
- ◊ FT - FE model w/Ethernet Interface



RE Model Shown