

MODEL 6006
1020 - 1550 MHz
150 WATTS
LINEAR POWER RF AMPLIFIER

Solid State
Band-specific High
Power RF Amplifier

The 6006 is a 150 Watt band-specific amplifier that covers the 1020-1550 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 6006 comes with an extended multiyear warranty.

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

CIRCUIT CONTROL

- ◇ Standby (amplifier disable)
- ◇ Gain/power setting with 25dB range
- ◇ VSWR protection Reset
- ◇ ALC On/ Off

CIRCUIT INDICATIONS

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

ORDERING MODELS

- ◇ RE - R model with Ethernet, IEEE488 and RS232
- ◇ FE - F model with Ethernet, IEEE488 and RS232

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	1020-1550 MHz
2	Saturated Output Power	150 Watts typical
3	Power Output @ 1dB Comp.	80 Watts min
4	Small Signal Gain	+50 dB min
5	Small Signal Gain Flatness	± 1.0 dB max
6	IP ₃	+59 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc Minimum
9	Spurious Signals	< -60 dBc Minimum
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	800 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	Pulse
15	Class of Operation	A/AB
16	Duty Cycle	1%
17	Pulse Width	500nSec
18	Rise/Fall Time	150nSec
Mechanical		
19	Dimensions	19" x 7.0" x 20"
20	Weight	50 lb. max
21	RF Connectors	Type-N
22	Grounding	Chassis
23	Cooling	Internal Forced Air
Environmental		
24	Operating Temperature	0° C to +50° C
25	Operating Humidity	95% Non-condensing
26	Operating Altitude	Up to 10,000' Above Sea Level
27	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice



FE Model Shown