



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5085-001

10 kHz - 250 MHz
100 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5085 is a 100 Watt broadband amplifier that covers the 10 kHz – 250 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5085 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	0.01 – 250 MHz
2	Saturated Output Power	100 Watts typical
3	Power Output @ 1dB Comp.	75 Watts typical 60 Watts min
4	Small Signal Gain	+50 dB min
5	Small Signal Gain Flatness	± 2.5 dB max
6	IP ₃	+54 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-15 dBc typical @ 75 Watts
9	Spurious Signals	< -60 dBc typical @ 75 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	700 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<u>Mechanical</u>		
16	Dimensions	19" x 8.75" x 20"
17	Weight	75 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



FE Model Shown

ORDERING MODELS

- ◇ RE - Rear RF Connector model with Ethernet, IEEE488 and RS232
- ◇ FE - Front RF Connector model with Ethernet, IEEE488 and RS232
- ◇ R - Rear RF Connector model
- ◇ F - Front RF Connector model