



FTP-14BH

HIGH CURRENT BIAS TAP



The FTP-14BH Bias Tap is used to provide a DC path to one side of a 50 Ohm transmission line. An integral blocking capacitor isolates the DC from the other side of the line.

SPECIFICATIONS

Frequency Range	30 - 512 MHz
Insertion Loss	0.20 dB maximum
VSWR	1.3:1 maximum
RF Power	200 W CW maximum
DC Resistance	0.1 Ohm maximum
DC Voltage	200 Volts maximum
DC Current	10 A maximum
Connectors: DC	MS3102R10SL-3P
RF	Type N-male
RF+DC	Type N-female
Size, excluding connectors	1.16" x 1.06" x 1.00"
Weight	123 grams nominal

OPTION: FTP-14BHR – Provides the DC path to the N-male connector, instead of the N-female connector.