



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5030

20 - 500 MHz
500 WATTS

Solid State Broadband High Power RF Amplifier

The 5030 is a 500 Watt broadband amplifier that covers the 20 – 500 MHz frequency range. This amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this unit achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5030 comes with an extended multiyear

	Parameter	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	20 – 500 MHz
2	Saturated Output Power	500 Watts typical
3	Power Output @ 1dB Comp.	300 Watts min
4	Small Signal Gain	+58 dB min
5	Gain Flatness	± 2.0 dB
6	IP ₃	+61 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-15 dBc typical @ 300 Watts
9	Spurious Signals	> -60 dBc typical @ 300 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	6000 Watts max
12	AC Input	186 – 264 VAC, single phase
13	RF Input	0 dB max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<u>Mechanical</u>		
16	Dimensions	19" x 10.5" x 24" (TBD)
17	Weight	350 lbs.
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport <small>Specifications subject to change without notice.</small>

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

ORDERING MODELS

- ◇ R - Rear Panel Connectors
- ◇ F - Front Panel Connectors
- ◇ RE - R model w/Control Option
- ◇ FE - F model w/Control Option
- ◇ RT - RE model w/Ethernet Interface
- ◇ FT - FE model w/Ethernet Interface



RE Model Shown

Approved By: _____ Date: _____