



5300 Beethoven Street, Los Angeles, CA 90066  
TEL: (310)306-5556 • FAX: (310)577-9887  
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5803032

**0.5 - 500 MHz**  
**8 WATTS**  
**LINEAR POWER RF AMPLIFIER**

### **Solid State Broadband High Power RF Amplifier**

The 5803032 is an 8 Watt broadband amplifier that covers the 0.5 – 500 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 5803032 comes with an extended

	Parameter	Specification @ 25° C
<b>Electrical</b>		
1	Frequency Range	0.5 – 500 MHz
2	Saturated Output Power	8 Watts typical
3	Power Output @ 1dB Comp.	4 Watts min
4	Small Signal Gain	+40 dB min
5	Gain Flatness	± 1.0 dB max
6	IP <sub>3</sub>	+42 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 4 Watts
9	Spurious Signals	< -60 dBc typical @ 4 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	3 Amps max
12	DC Input	28 VDC nominal
13	RF Input	-1 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<b>Mechanical</b>		
16	Dimensions	6" x 3" x 3.5"
17	Weight	6 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Cooling Required
<b>Environmental</b>		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

### **INCLUDED FEATURES**

- ◇ Mounted on a Heat Sink with fans