



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4061-001

1637 - 2034 MHz
 200 WATTS
 LINEAR POWER RF AMPLIFIER

Solid State Band-specific High Power RF Amplifier

The 4061-001 is a 200 Watt band-specific amplifier that covers the 1637 – 2034 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 4061-001 comes with an extended

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Bands	1637–1643, 2024–2034 MHz
2	Saturated Output Power	200 Watts typical
3	Power Output @ 1dB Comp.	160 Watts min
4	Small Signal Gain	+53 dB min
5	Small Signal Gain Flatness	± 0.25 dB max for each band
6	IP ₃	+62 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 160 Watts
9	Spurious Signals	< -60 dBc typical @ 160 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	1100 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	19" x 7.0" x 20"
17	Weight	60 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

CIRCUIT PROTECTIONS

- ◊ Thermal Overload
- ◊ Over Current
- ◊ Over Voltage

ORDERING MODELS

- ◊ RE - R model w/Control Option
- ◊ FE - F model w/Control Option
- ◊ RT - RE model w/Ethernet Interface
- ◊ FT - FE model w/Ethernet Interface



RE Model Shown