



5300 Beethoven Street, Los Angeles, CA 90066  
TEL: (310)306-5556 • FAX: (310)821-7413  
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5072-001

**80 - 1000 MHz  
280 WATTS  
LINEAR POWER RF AMPLIFIER**

### Solid State Broadband High Power RF Amplifier

The 5072-001 is a 280 Watt broadband amplifier that covers the 80 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability.

### CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ VSWR

	Parameter	Specification @ 25° C
<b>Electrical</b>		
1	Frequency Range	80 – 1000 MHz
2	Saturated Output Power	280 Watts typical
3	Power Output @ 1dB Comp.	150 Watts min
4	Small Signal Gain	+56 dB min
5	Gain Flatness	± 2.0 dB
6	IP <sub>3</sub>	+58 dBm
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical
9	Spurious Signals	-60 dBc typical
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	3000 Watts max
12	AC Input	186 – 264 VAC, three phase
13	Nominal RF Input	0 dBm
14	RF Input Overdrive	+0 dBm max
15	RF Input Signal Format	CW/AM/FM/PM/Pulse
16	Class of Operation	AB
<b>Mechanical</b>		
17	Dimensions (W x H x D)	19" x 8.75" x 20"
18	Weight	80 lb. max
19	Input/Output RF Connectors	Type-N
20	Grounding	Chassis
21	Cooling	Internal Forced Air
<b>Environmental</b>		
22	Operating Temperature	0° C to +50° C
23	Operating Humidity	95% Non-condensing
24	Operating Altitude	Up to 10,000' Above Sea Level
25	Shock and Vibration	Normal Truck Transport

### ORDERING MODELS

- ◇ RE - Rear Panel with RS232 & IEEE
- ◇ FE - Front Panel with RS232 & IEEE
- ◇ RT - Rear Panel with Ethernet Interface
- ◇ FT - Front Panel with Ethernet Interface

### OTHER FEATURES

- ◇ RF output Coupling port @ 53dB below peak power