



## WR-51 to SMA Female Waveguide to Coax Adapter 15 GHz to 22 GHz

### **TECHNICAL DATA SHEET**

PE9845

#### WR-51 to SMA Female Waveguide to Coax Adapter 15 GHz to 22 GHz

Configuration

Waveguide Interface WR-51
RF Connector SMA Female
RF Connector Impedance 50 Ohms
Body Style End Launch

**Electrical Specifications** 

Frequency Range, GHz 15 to 22 Maximum VSWR 1.45:1

#### **Mechanical Specifications**

Size

 Length, in [mm]
 1.161 [29.49]

 Width/Dia., in [mm]
 1.325 [33.66]

 Height, in [mm]
 1.325 [33.66]

**Waveguide Interface** 

Type WR-51
Body Material and Plating Aluminum

**RF Connector** 

Type SMA Female

Body Material and Plating Passivated Stainless Steel

Compliance Certifications (visit www.Pasternack.com for current document)

#### Plotted and Other Data

Notes: Values at 25 °C, sea level

WR-51 to SMA Female Waveguide to Coax Adapter 15 GHz to 22 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-51 to SMA Female Waveguide to Coax Adapter 15 GHz to 22 GHz PE9845

URL: http://www.pasternack.com/wr-51-sma-female-end-launch-waveguide-coax-adapter-15-ghz-22-ghz-pe9845-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.



# PE9845 CAD Drawing

WR-51 to SMA Female Waveguide to Coax Adapter 15 GHz to 22 GHz

