



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4037

**200 - 475 MHz
 800 WATTS
 LINEAR POWER RF AMPLIFIER**

Solid State Band-Specific High Power RF Amplifier

The 4037 is an 800 Watt band-specific amplifier that covers the 200 – 475 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 4037 comes with an extended multiyear

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	200 – 475 MHz
2	Saturated Output Power	800 Watts typical
3	Power Output @ 1dB Comp.	500 Watts min
4	Small Signal Gain	+59 dB min
5	Gain Flatness	± 2.0 dB
6	IP ₃	+63 dBm typical
7	Input VSWR	1.5:1 max
8	Harmonics	-20 dBc typical @ 500 Watts
9	Spurious Signals	< -60 dBc typical @ 500 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	6000 Watts max
12	AC Input	200 – 240 VAC, single phase
13	RF Input	0 dB max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions (with rack)	31" x 24" x 26"
17	Weight (with rack)	360 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



RE Model Shown

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

ORDERING MODELS

- ◇ RE - R model w/Control Option
- ◇ FE - F model w/Control Option
- ◇ RT - RE model w/Ethernet Interface
- ◇ FT - FE model w/Ethernet Interface