



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5902019

2.3 - 2.5 GHz

50 WATTS

LINEAR POWER RF AMPLIFIER

Solid State Band-specific High Power RF Amplifier

The 5902019 is a 50 Watt band-specific amplifier that covers the 2.3 – 2.5 GHz frequency range (100MHz Instantaneous Bandwidth). This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5902019 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	2.3 – 2.5 GHz
2	Instantaneous Bandwidth	100 MHz
3	Saturated Output Power	50 Watts typical
4	Power Output @ 1dB Comp.	40 Watts min
5	Small Signal Gain	+48 dB min
6	Gain Flatness	± 0.75 dB max
7	IP ₃	+56 dBm typical
8	Input VSWR	2:1 max
9	Harmonics	-20 dBc typical @ 40 Watts
10	Spurious Signals	< -60 dBc typical @ 40 Watts
11	Input/Output Impedance	50 Ohms nominal
12	DC Input Current	10.5 Amps max
13	DC Input	13 VDC nominal
14	RF Input	+10 dBm max
15	RF Input Signal Format	CW/AM/FM/PM/Pulse
16	Class of Operation	A/AB
Mechanical		
17	Dimensions	8.7" x 5.2" x 3.5"
18	Weight	6 lb. max
19	Connectors	SMA female
20	Grounding	Chassis
21	Cooling	Adequate Heatsink Required
Environmental		
22	Operating Temperature	0° C to +50° C
23	Operating Humidity	95% Non-condensing
24	Operating Altitude	Up to 10,000' Above Sea Level
25	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



FEATURES:

Heatsink included (not shown).
 Customized selection of Bandwidth (100MHz inside 2.3 - 2.5 GHz)..