



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5303055-006

5 - 145 MHz
40 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5303055-006 is a 40 Watt broadband amplifier that covers the 5 - 145 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5303055-006 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	5 - 145 MHz
2	Saturated Output Power	40 Watts Typical
3	Power Output @ 1dB Comp.	25 Watts min
4	Small Signal Gain	+46 dB min
5	Gain Flatness	± 1.0 dB max
6	IP ₃	+50 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-15 dBc typical @ 20 Watts
9	Spurious Signals	< -60 dBc typical @ 20 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	5 Amps max
12	DC Input	28 VDC nominal
13	RF Input	+1 dBm
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
Mechanical		
16	Dimensions	6" x 3" x 1.1"
17	Weight	2 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
Environmental		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

OPTIONS AVAILABLE

- ◇ - Heat Sink
- ◇ - Heat Sink and Fans
- ◇ - Expanded Temperature Range to -40° to +85° C

