



5300 Beethoven Street, Los Angeles, CA 90066

TEL: (310)306-5556 • FAX: (310)577-9779

WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5803007-002

380 - 470 MHz

125 WATTS

Solid State Broadband High Power RF Amplifier

The 5803007-002 is a 125 Watt broadband amplifier that covers the 380 – 470 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5803007-002 comes with an extended

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	380 – 470 MHz
2	Saturated Output Power	125 Watts typical
3	Power Output @ 1dB Comp.	80 Watts min
4	Small Signal Gain	+11 dB min
5	Gain Flatness	± 1.5 dB max
6	IP ₃	+55 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 80 Watts
9	Spurious Signals	> -60 dBc typical @ 80 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	15 Amps max
12	DC Input	28 VDC nominal
13	RF Input	+42 dBm
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
Mechanical		
16	Dimensions (w/Heatsink)	8.7" x 5.2" x 3.6"
17	Weight (w/Heatsink)	6 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Airflow Required
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



FEATURES:

Heatsink and Fans Included (Not Shown)