



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5054

1.0 - 3.0 GHz
15 WATTS

Solid State Broadband High Power RF Amplifier

The 5054 is a 15 Watt broadband amplifier that covers the 1.0 – 3.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5054 comes with an extended multiyear

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	1.0 – 3.0 GHz
2	Saturated Output Power	15 Watts typical
3	Power Output @ 1dB Comp.	10 Watts min
4	Small Signal Gain	+42 dB min
5	Small Signal Gain Flatness	± 2.0 dB max
6	IP ₃	+50 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 10 Watts
9	Spurious Signals	> -60 dBc typical @ 10 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	120 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	19" x 3.5" x 18"
17	Weight	28 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

CIRCUIT PROTECTIONS

- ◇ Infinite Load VSWR
- ◇ Thermal Overload
- ◇ Over Current

ORDERING MODELS

- ◇ R - Rear Panel Connectors
 - ◇ F - Front Panel Connectors
 - ◇ RE - R model w/Control Option
 - ◇ FE - F model w/Control Option
 - ◇ RT - RE model w/Ethernet Interface
 - ◇ FT - FE model w/Ethernet Interface
- RE Model Shown

