



5300 Beethoven Street, Los Angeles, CA 90066

TEL: (310)306-5556 • FAX: (310)577-9887

WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5067-001

200 - 1000 MHz

300 WATTS

### Solid State Broadband High Power RF Amplifier

The 5067-001 is a 300 Watt broadband amplifier that covers the 200 – 1000 MHz frequency range. This amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 5067-001 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
<b>Electrical</b>		
1	Frequency Range	200 – 1000 MHz
2	Saturated Output Power	300 Watts typical
3	Power Output @ 1dB Comp.	200 Watts min
4	Small Signal Gain	+56 dB min
5	Gain Flatness	± 2.0 dB max
6	IP <sub>3</sub>	+58 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 200 Watts
9	Spurious Signals	> -60 dBc typical @ 200 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	6000 Watts max
12	AC Input	186 – 264 VAC, three phase
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<b>Mechanical</b>		
16	Dimensions	31" x 24" x 26"
17	Weight	360 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<b>Environmental</b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

### CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

### ORDERING MODELS

- ◇ F - Front Panel Connectors
- ◇ FE - Front Panel Connectors  
and Control Option