



5300 Beethoven Street, Los Angeles, CA 90066

TEL: (310)306-5556 • FAX: (310)821-7413

WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5284

2.0 - 4.0 GHz

100 WATTS

LINEAR POWER RF AMPLIFIER

### Solid State Broadband High Power RF Amplifier

The 5284 is a 100 Watt broadband amplifier that covers the 2.0 – 4.0 GHz frequency range. This small and lightweight amplifier utilizes Class A linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 5284 comes with an extended multiyear warranty backed by Ophir RF's commitment to total customer satisfaction.

	Parameter	Specification @ 25° C
<b>Electrical</b>		
1	Frequency Range	2.0 – 4.0 GHz
2	Saturated Output Power	100 Watts Minimum
3	P1dB Output Power	60 Watts Minimum
4	Small Signal Gain	+50 dB min
5	Power Flatness	± 2.0 dB max
6	IP <sub>3</sub>	+56 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 60 watts
9	Spurious Signals	< -60 dBc typical @ 60 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	800 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A
<b>Mechanical</b>		
16	Dimensions	19" x 5.25" x 20"
17	Weight	46 Lbs.
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<b>Environmental</b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice



FE Model Shown

### ORDERING MODELS

- ◇ **R** - Rear Panel Connector Model
- ◇ **F** - Front Panel Connector Model
- ◇ **RE** - Rear Panel Connector Model with Ethernet, IEEE488 and RS232 Communication Ports
- ◇ **FE** - Front Panel Connector Model with Ethernet, IEEE488 and RS232 Communication Ports

Approved By: \_\_\_\_\_ Date: \_\_\_\_\_



5300 Beethoven Street, Los Angeles, CA 90066  
TEL: (310)306-5556 • FAX: (310)821-7413  
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5284

2.0 - 4.0 GHz  
100 WATTS  
LINEAR POWER RF AMPLIFIER

### FRONT PANEL CONTROLLER FEATURES

- ◇ Forward Power Monitoring
- ◇ Reflected Power Monitoring
- ◇ Gain Control (Continuously Variable VVA 20dB)
- ◇ Fault Status
- ◇ Full Protection Of any VSWR Condition, Open or Short, into any Phase Angle
- ◇ Remote Control Access via the Ethernet, RS-232, or IEEE-488 Communications ports
- ◇ Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, phase or input RF level
- ◇ Standby/Enable Control
- ◇ Front Panel Display for easy viewing of System Status Locally
- ◇ Keypad buttons for full local control

### CIRCUIT CONTROL (WITH FRONT PANEL CONTROLLER)

- ◇ Standby (amplifier disable)
- ◇ Gain/power setting with 20dB range
- ◇ VSWR protection Reset
- ◇ ALC On/ Off

### CIRCUIT INDICATIONS (WITH FRONT PANEL CONTROLLER)

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

### CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ Open or Short VSWR Conditions (With Front Panel Controller)

### RFPA SYSTEM OPTIONS

- ◇ Switched Filter Bank
- ◇ Input Power Requirements
- ◇ Ruggedized Version
- ◇ Cabinet Requirements
- ◇ Outdoor Version
- ◇ Sample Ports
- ◇ Racking Options
- ◇ Many More!
- ◇ **Consult Factory with Specific Requirements**

