

SPECIFICATION SHEET
JFW MODEL 50KFA-074 BNC
FIXED ATTENUATOR KIT

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range DC-2200 MHz

Impedance 50 Ohms nominal

RF Connectors BNC

RF Input Power 1 Watt average

Parts Included (1 piece) 3dB fixed attenuator, BNC male/female
(1 piece) 6dB fixed attenuator, BNC male/female
(1 piece) 10dB fixed attenuator, BNC male/female
(1 piece) 20dB fixed attenuator, BNC male/female
(1 piece) Termination BNC male

Model Numbers for Each Individual Part

50F-003 BNC	(3dB Fixed Attenuator)
50F-006 BNC	(6dB Fixed Attenuator)
50F-010 BNC	(10dB Fixed Attenuator)
50F-020 BNC	(20dB Fixed Attenuator)
50T-319 BNC M	(Termination)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	09/24/2014		TRS 09/24/2014				