

5300 Beethoven Street, Los Angeles, CA 90066 TEL: (310)306-5556 • FAX: (310)821-7413 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5006-005

200 - 500 MHz 500 WATTS LINEAR POWER RF AMPLIFIER

Specification @ 25° C

Solid State Broadband High Power RF Amplifier

The 5006-005 is a 500 Watt broadband amplifier that covers the 200 – 500 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most devices advanced and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} the 5006-005 amplifiers, comes with an extended multiyear warranty.

The contract of the contract o	<u>Parameter</u>	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	200 – 500 MHz
2	Saturated Output Power	500 Watts typical
3	Power Output @ 1dB Comp.	300 Watts min
4	Small Signal Gain	+58 dB min
5	Gain Flatness	<u>+</u> 2.0 dB
6	IP ₃	+61 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 300 Watts
9	Spurious Signals	< -60 dBc typical @ 300 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	3000 Watts max
12	AC Input	200 – 240 VAC, single phase
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<u>Mechanical</u>		
16	Dimensions	19" x 8.75" x 20"
17	Weight	80 lb. max
18	Connectors	Type-N
19	Rack Mountable Slides and Support Bracket	18" slides (37" wingspan)
20	Grounding	Chassis
21	Cooling	Internal Forced Air
<u>Environmental</u>		
22	Operating Temperature	0° C to +50° C
23	Operating Humidity	95% Non-condensing
24	Operating Altitude	Up to 10,000' Above Sea Level
25	Shock and Vibration	Normal Truck Transport
Specifications subject to change without notice		

Parameter

Specifications subject to change without notice.

CIRCUIT CONTROL

- ♦ Standby (amplifier disable)
- ♦ Gain/power setting with 25dB range
- ♦ VSWR protection Reset
- ♦ ALC On/ Off

CIRCUIT INDICATIONS

- ♦ Forward Power
- ♦ Reflected power
- ♦ VSWR Fault

07/11

- ♦ Temp Fault
- ♦ Gain Setting (VVA) percentage

CIRCUIT PROTECTIONS

- ♦ Thermal Overload
- ♦ Over Current
- ♦ Over Voltage

FE Model Shown

ORDERING MODELS

- ♦ RE R model with Ethernet, IEEE488 and RS232
- ♦ FE F model with Ethernet, IEEE488 and RS232

Approved By: Date: