



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5302030-010

1.8 - 2.0 GHz

30 WATTS

LINEAR POWER RF AMPLIFIER

Solid State Band-specific High Power RF Amplifier

The 5302030-010 is a 30 Watt amplifier that covers the 1.8 – 2.0 GHz frequency range. This small and light-weight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5302030-010 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	1.8 – 2.0 GHz
2	Output Protection	Open and Short
3	Saturated Output Power	30 Watts typical
4	Power Output @ 1dB Comp.	25 Watts min
5	Small Signal Gain	+45 dB min
6	Gain Flatness	± 1.0 dB max
7	IP ₃	+54 dBm typical
8	Input VSWR	2:1 max
9	Harmonics	-20 dBc typical @ 25 Watts
10	Spurious Signals	< -60 dBc typical @ 25 Watts
11	Input/Output Impedance	50 Ohms nominal
12	DC Input Current	8 Amps max
13	DC Input	13 VDC nominal
14	RF Input	+10 dBm max
15	RF Input Signal Format	CW/AM/FM/PM/Pulse
16	Class of Operation	A/AB
Mechanical		
17	Dimensions	6.55" x 4" x 1.1"
18	Weight	3 lb. max
19	Connectors	SMA female
20	Grounding	Chassis
21	Cooling	Adequate Heatsink and Airflow Required
Environmental		
22	Operating Temperature	0° C to +50° C
23	Operating Humidity	95% Non-condensing
24	Operating Altitude	Up to 10,000' Above Sea Level
25	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



Shutdown:

+5V (Disable)
GND or Open (Enable)

Output Protection:

Can operate into a full Open or Short, without damage, due to the use of an Internal Circulator and Load.