



WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz

TECHNICAL DATA SHEET

PE9883

WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz

Configuration

Waveguide Interface WR-90
Flange Design Standard
RF Connector N Female

Electrical Specifications

Frequency Range, GHz
Maximum VSWR

8.2 to 12.4
1.25:1

Mechanical Specifications

Size

 Length, in [mm]
 1.5 [38.1]

 Width/Dia., in [mm]
 2.09 [53.09]

 Height, in [mm]
 1.6 [40.64]

Waveguide Interface

Type WR-90
Body Material and Plating Aluminum

RF Connector

Type N Female

Compliance Certifications (visit www.Pasternack.com for current document)

RoHS Compliant Yes

Plotted and Other Data

Notes: Values at 25 °C, sea level

WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz PE9883

URL: http://www.pasternack.com/wr-90-n-female-waveguide-coax-adapter-8.2-12.4-ghz-pe9883-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.



PE9883 CAD Drawing

WR-90 to N Female Waveguide to Coax Adapter 8.2 GHz to 12.4 GHz

