

High Power

50Ω 14dB Coupling DC Pass 1750 to 2700 MHz



Operating Temperature	-55°C to 100°C
Storage Temperature	-55°C to 100°C
DC Current	2A

Permanent damage may occur if any of these limits are exceeded.

INPUT	1
OUTPUT	2
COUPLED (forward)	4
COUPLED (reverse)	3
GROUND	5

Technical drawing of a cross-section of a metal part. The part has a central rectangular section with a width of .500 TYP and a height of .175. This central section is flanked by two side sections, each with a width of .175. The total width of the part is .670. The top surface of the central section is .060 TYP thick. The bottom surface of the central section is .067 TYP thick. The side sections have a height of .295. The total height of the part is .275. A hatched area indicates METALLIZATION. Dimensions are given in inches.

Outline Dimensions (inch/mm)

A	B	C	D	E	F	G
.70	.32	.13	.060	.100	.500	.022
17.78	8.13	3.30	1.52	2.54	12.70	0.56
H	J	K	L	M		wt
.060	.040	.360	.670	.175		grams
1.52	1.02	9.14	17.02	4.45		0.68

[illegible]

NOTES: 1. TRACE WIDTH IS SHOWN FOR ROGERS RO4350B WITH DIELECTRIC THICKNESS .030" ± .002"; COPPER: 1/2 OZ. EACH SIDE.
FOR OTHER MATERIALS TRACE WIDTH MAY NEED TO BE MODIFIED.
2. BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.

	DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)
	DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MC/Store/terms.jsp

- high power handling, 50 watts at room temp.
- low mainline loss, 0.3 dB typ.
- excellent VSWR, 1.10:1 typ.
- excellent directivity 23 dB typ.
- wideband frequency, 1750 to 2700 MHz

- PCS
- ISM
- cable TV relay
- defense communications
- federal communications

FREQ. (MHz)	COUPLING (dB)		MAINLINE LOSS¹ (dB)		DIRECTIVITY (dB)		VSWR (:1)	POWER INPUT (W)
f _c -f _u	Nom.	Flatness	Typ.	Max.	Typ.	Min.	Typ.	Max.
1750-2700			0.40	0.75	23	16	1.15	
1750-1950	15.1±0.7	±0.6	0.25	0.55	23	18	1.10	25
1950-2300	14.5±0.8	±0.7	0.30	0.65	23	17	1.15	25
2300-2700	13.5±0.8	±0.7	0.45	0.75	23	16	1.10	25

Frequency (MHz)	Mainline Loss (dB)	Coupling (dB)		Directivity (dB)		Return Loss (dB)			
	In-Out	In-Cpl Fwd	Out-Cpl Rev	Out-Cpl Fwd	In-Cpl Rev	In	Out	Cpl Fwd	Cpl Rev
1750.00	0.24	15.48	15.44	24.90	25.49	34.46	42.66	36.15	34.86
1850.00	0.26	15.10	15.06	24.67	25.03	29.56	34.99	31.27	30.35
1950.00	0.28	14.73	14.69	24.37	24.88	26.11	29.65	28.29	27.70
2150.00	0.34	14.12	14.08	23.78	24.57	22.20	24.32	24.71	24.20
2300.00	0.38	13.73	13.69	23.34	24.13	20.48	22.19	23.35	22.65
2350.00	0.40	13.61	13.57	23.37	24.19	20.22	21.87	23.20	22.65
2450.00	0.41	13.36	13.33	22.76	23.69	19.67	21.28	23.02	22.26
2550.00	0.44	13.12	13.09	22.39	23.60	19.54	21.24	23.16	22.30
2650.00	0.44	12.87	12.82	21.93	23.45	19.62	21.65	23.64	22.75
2700.00	0.46	12.77	12.71	21.83	23.49	19.88	22.04	24.16	23.40

Frequency (MHz)	Mainline Loss (dB)
1750	0.25
1940	0.28
2130	0.33
2320	0.40
2510	0.44
2700	0.45

Frequency (MHz)	Coupling IN-CPL FWD (dB)	Directivity IN-CPL-REV (dB)
1750	15	25
1940	14	24
2130	13	23
2320	12	22
2510	11	21
2700	12	22

Frequency (MHz)	IN (dB)	OUT (dB)	CPL-FWD (dB)	CPL-REV (dB)
1750	35	42	32	30
1940	28	32	28	26
2130	24	26	24	23
2320	21	23	22	21
2510	20	22	22	21
2700	21	23	23	22

BI-DIRECTIONAL COUPLER
(DC THRU)*

DC+RF INPUT

DC+RF OUTPUT

The diagram shows a rectangular block representing the coupler. Two horizontal lines enter from the left, labeled 'DC+RF INPUT'. Two horizontal lines exit to the right, labeled 'DC+RF OUTPUT'. Inside the block, there are two curved arrows pointing downwards from the input lines to the output lines, indicating a signal path or coupling mechanism.

REV. A
M119986
ED-12762/2
SYBD-14-272HP+
WZ/QL/AM
120917