



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5304032

2.5 - 6.0 GHz
50 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5304032 is a 50 Watt broadband amplifier that covers the 2.5 - 6.0 GHz frequency range. This small and lightweight amplifier utilizes Class A linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5304032 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	2.5 - 6.0 GHz
2	Saturated Output Power	50 Watts min
3	Small Signal Gain	+46 dB min
4	Gain Flatness	± 1.5 dB max
5	IMP ₃	-65dBc @ 20dBm Output
6	Input VSWR	2:1 max
7	Harmonics	-20 dBc typical
8	Spurious Signals	< -60 dBc typical
9	Noise Figure	3.0dB
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	11.0A Max
12	DC Input	24 VDC nominal
13	RF Input	-20 dBm nominal
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A
<u>Mechanical</u>		
16	Dimensions	6" x 4" x 1"***
17	Weight	2 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
<u>Environmental</u>		
21	Baseplate Temperature	-40° C to +85° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	MIL-STD-810F

Specifications subject to change without notice



**Size of 5304030, 5304031, and 5304032 can be modified to be identical