




## MATERIALS


|                |                     |
|----------------|---------------------|
| BODY           | BRASS NICKEL PLATED |
| CONTACT        | GOLD PLATED         |
| INSULATOR      | PTFE                |
| SOLDER ADAPTER | BRASS GOLD PLATED   |



MOUNTING HOLE



ASSEMBLY (A)



ASSEMBLY (B)

## ASSEMBLY PROCEDURES

1. SLIDE CLAMP NUT (1), WASHER (2) & GASKET (3) OVER CABLE. STRIP CABLE AS SHOWN IN ASSEMBLY (A). DO NOT CUT DIELECTRIC.
2. SLIDE ADAPTER (4) OVER CABLE UNTIL ADAPTER (4) BOTTOMS ON OUTER CONDUCTOR. SOLDER ADAPTER (4) TO OUTER CONDUCTOR USING MINIMUM HEAT.
3. STRIP CABLE AS SHOWN IN ASSEMBLY (B). SOLDER CONTACT TO CENTER CONDUCTOR. SLIDE ASSEMBLY FORWARD & TIGHTEN TO BODY.



**PASTERNAK ENTERPRISES, INC.**

P.O BOX 16759, IRVINE, CA 92623  
PHONE (949) 261-1920 FAX (949) 261-7451

WEB ADDRESS: [www.pasternack.com](http://www.pasternack.com)  
E-MAIL ADDRESS: [sales@pasternack.com](mailto:sales@pasternack.com)

**COAXIAL & FIBER OPTICS**

DWG TITLE

**PE4754**

DES.

REVERSE POLARITY BNC FEMALE,  
BULKHEAD, SOLDER/CLAMP ATTACHMENT  
FOR RG402, PE-SR402AL & PE-SR402FL

SIZE A

**FSCM NO. 53919**

CAD FILE

060602

SCALE N/A

127

## NOTES:

1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.