

## High Power

50Ω    22dB Coupling    DC Pass    1400 to 1750 MHz



|                                                                 |                |
|-----------------------------------------------------------------|----------------|
| Operating Temperature                                           | -55°C to 100°C |
| Storage Temperature                                             | -55°C to 100°C |
| DC Current                                                      | 2A             |
| Permanent damage may occur if any of these limits are exceeded. |                |

|                   |   |
|-------------------|---|
| INPUT             | 1 |
| OUTPUT            | 2 |
| COUPLED (forward) | 4 |
| COUPLED (reverse) | 3 |
| GROUND            | 5 |

Figure 1 is a technical drawing showing the detail of the test specimen. The drawing includes the following dimensions and features:

- Overall width: .670 TYP
- Core width: .360 TYP
- Top layer thickness: .067 TYP
- Core thickness: .175 TYP
- Bottom layer thickness: .067 TYP
- Overall height: .295 TYP
- Gap around specimen: .060 TYP
- Centerline symbol (C) is indicated.
- A hatched area represents METALLIZATION.

### Outline Dimensions (inch)

|       |      |      |       |      |       |       |
|-------|------|------|-------|------|-------|-------|
| A     | B    | C    | D     | E    | F     | G     |
| .70   | .32  | .13  | .060  | .100 | .500  | .022  |
| 17.78 | 8.13 | 3.30 | 1.52  | 2.54 | 12.70 | 0.56  |
| H     | J    | K    | L     | M    |       | wt    |
| .060  | .040 | .360 | .670  | .175 |       | grams |
| 1.52  | 1.02 | 9.14 | 17.02 | 4.45 |       | 0.68  |

NOTES: 1. TRACE WIDTH IS SHOWN FOR ROGERS RO4350B WITH DIELECTRIC THICKNESS .030" .002" COPPER: 1/2 OZ. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH MAY NEED BE MODIFIED.

2. BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.

 DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)

 DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

1. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.

2. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.

3. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at [www.minicircuits.com/MCLStore/terms.jsp](http://www.minicircuits.com/MCLStore/terms.jsp)

- high power handling, 50 watts typ.
- low mainline loss, 0.09 dB typ.
- excellent VSWR, 1.15:1 typ.
- good directivity, 24 dB typ.
- wideband frequency, 1400 to 1750 MHz

- GPS
- instrumentation
- defense communications
- federal communications

| FREQ.<br>(MHz) | COUPLING<br>(dB) |          | MAINLINE LOSS'<br>(dB) |      | DIRECTIVITY<br>(dB) |      | VSWR<br>(:1) | POWER<br>INPUT<br>(W) |
|----------------|------------------|----------|------------------------|------|---------------------|------|--------------|-----------------------|
| $f_u - f_l$    | Nom.             | Flatness | Typ.                   | Max. | Typ.                | Min. | Typ.         | Max.                  |
| 1400-1750      |                  |          | 0.09                   | 0.30 | 20                  | 16   | 1.15         |                       |
| 1400-1580      | 22.3±0.7         | ±0.7     | 0.07                   | 0.30 | 24                  | 17   | 1.15         | 50                    |
| 1580-1750      | 21.5±0.7         | ±0.6     | 0.09                   | 0.30 | 23                  | 16   | 1.15         | 25                    |

1. Mainline loss includes theoretical power loss at coupled port.

| Frequency<br>(MHz) | Mainline Loss<br>(dB) | Coupling<br>(dB) |             | Directivity<br>(dB) |            | Return Loss<br>(dB) |       |         |         |
|--------------------|-----------------------|------------------|-------------|---------------------|------------|---------------------|-------|---------|---------|
|                    | In-Out                | In-Cpl Fwd       | Out-Cpl Rev | Out-Cpl Fwd         | In-Cpl Rev | In                  | Out   | Cpl Fwd | Cpl Rev |
| 1400.00            | 0.05                  | 23.00            | 23.02       | 24.67               | 25.14      | 25.39               | 24.98 | 28.86   | 28.19   |
| 1440.00            | 0.06                  | 22.79            | 22.81       | 24.57               | 25.18      | 25.07               | 24.66 | 28.59   | 27.83   |
| 1480.00            | 0.06                  | 22.58            | 22.60       | 24.38               | 24.89      | 24.65               | 24.38 | 28.07   | 27.33   |
| 1520.00            | 0.07                  | 22.38            | 22.40       | 24.30               | 24.81      | 24.35               | 24.10 | 27.87   | 27.35   |
| 1580.00            | 0.07                  | 22.08            | 22.10       | 24.13               | 24.51      | 24.06               | 23.84 | 27.66   | 26.89   |
| 1620.00            | 0.08                  | 21.90            | 21.92       | 23.75               | 24.17      | 23.84               | 23.64 | 27.26   | 26.71   |
| 1660.00            | 0.08                  | 21.73            | 21.74       | 23.75               | 24.10      | 23.77               | 23.61 | 27.41   | 26.96   |
| 1670.00            | 0.08                  | 21.68            | 21.70       | 23.84               | 24.08      | 23.76               | 23.64 | 27.49   | 26.93   |
| 1710.00            | 0.09                  | 21.52            | 21.53       | 23.80               | 24.04      | 23.71               | 23.59 | 27.44   | 26.69   |
| 1750.00            | 0.09                  | 21.35            | 21.36       | 23.73               | 24.00      | 23.64               | 23.52 | 27.29   | 26.85   |

The graph shows the Mainline Loss in dB across the frequency range from 1400 MHz to 1700 MHz. The loss is consistently low, staying below 0.1 dB. There is a slight increase in loss as frequency increases, particularly above 1600 MHz.

| Frequency (MHz) | Mainline Loss (dB) |
|-----------------|--------------------|
| 1400            | 0.05               |
| 1450            | 0.06               |
| 1500            | 0.06               |
| 1550            | 0.07               |
| 1600            | 0.08               |
| 1650            | 0.08               |
| 1700            | 0.09               |

| Frequency (MHz) | Coupling IN-CPL FWD (dB) | Directivity IN-CPL-REV (dB) |
|-----------------|--------------------------|-----------------------------|
| 1400            | 22.0                     | 24.0                        |
| 1450            | 22.0                     | 23.5                        |
| 1500            | 22.0                     | 23.0                        |
| 1550            | 22.0                     | 22.5                        |
| 1600            | 22.0                     | 22.0                        |
| 1650            | 22.0                     | 22.0                        |
| 1700            | 22.0                     | 22.0                        |

| Frequency (MHz) | IN (dB) | OUT (dB) | CPL-FWD (dB) | CPL-REV (dB) |
|-----------------|---------|----------|--------------|--------------|
| 1400            | 25.5    | 25.5     | 28.5         | 28.5         |
| 1470            | 25.0    | 25.0     | 28.0         | 28.0         |
| 1540            | 24.5    | 24.5     | 27.5         | 27.5         |
| 1610            | 24.0    | 24.0     | 27.0         | 27.0         |
| 1680            | 24.0    | 24.0     | 27.0         | 27.0         |
| 1750            | 24.0    | 24.0     | 27.0         | 27.0         |

**BI-DIRECTIONAL COUPLER (DC THRU)\***

DC+RF INPUT →

← DC+RF OUTPUT

COUPLED FORWARD DC+RF

COUPLED REVERSE DC+RF

\* ELECTRICAL SCHEMATIC IS FOR BI-DIRECTIONAL COUPLER WITHOUT INTERNAL TRANSFORMERS AND RESISTORS.

REV. B  
M149783  
ED-12832/3  
SYBD-22-172HP+  
WZ/CP/AM  
150126