



Waveguide Mixer Up Converter WR-10 From
75 GHz to 110 GHz, IF From DC to 18 GHz And LO Power
of +13 dBm, UG-387/U Flange, W Band

Waveguide Converters - PE13U1000

Features

- W Band (75 to 110 GHz) full waveguide up converter
- Broad IF Frequency Range: DC to 18 GHz
- LO Drive level: +13 dBm nominal
- RF & LO Ports: WR-10 with UG-387/U-MOD Flange
- Double Balanced design
- Low Capacitance GaAs Schottky Beam Lead diodes
- Gold Plated Compact Package Design
- Operating Temperature: 0°C to +50°C

Applications

- Transmitter Subsystems
- Military Communications
- Commercial Communications
- Instruments and Test Equipment

Description

The PE13U1000 is a full waveguide band up converter mixer with an LO and RF frequency range of 75 to 110 GHz (W Band). The IF frequency range is DC to 18 GHz with a nominal LO drive level of +13 dBm. The double balanced circuit design utilizes high performance GaAs Schottky beam lead diodes. Conversion loss is 9 dB typical and flat across the entire frequency band. The gold plated compact package design uses integrated WR-10 with UG-387/U-MOD waveguide flange interfaces for the RF and LO ports and a female SMA connector for the IF port.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	75		110	GHz
LO Frequency Range	75		110	GHz
IF Frequency Range	DC		18	GHz
Conversion Loss		9		dB
LO Port Power		13	15	dBm

Mechanical Specifications

Size	
Length	1.4 in [35.56 mm]
Width	0.75 in [19.05 mm]
Height	0.75 in [19.05 mm]
Weight	0.0625 lbs [28.35 g]

Configuration	
Design	Mixer Up Converter

Description	RF Port	LO Port	IF Port
Type	WR-10 UG-387/U	WR-10 UG-387/U	SMA Female

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [Waveguide Mixer Up Converter WR-10 From 75 GHz to 110 GHz, IF From DC to 18 GHz And LO Power of +13 dBm, UG-387/U Flange, W Band PE13U1000](#)



Waveguide Mixer Up Converter WR-10 From
75 GHz to 110 GHz, IF From DC to 18 GHz And LO Power
of +13 dBm, UG-387/U Flange, W Band

Waveguide Converters - PE13U1000

Environmental Specifications

Temperature

Operating Range

0 to +50 deg C




Compliance Certifications (visit www.Pasternack.com for current document)

Not RoHS Compliant

Plotted and Other Data

Notes:


Typical Performance Data



Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [Waveguide Mixer Up Converter WR-10 From 75 GHz to 110 GHz, IF From DC to 18 GHz And LO Power of +13 dBm, UG-387/U Flange, W Band PE13U1000](#)

PE13U1000 CAD Drawing

Waveguide Mixer Up Converter WR-10 From 75 GHz to 110 GHz, IF From DC to 18 GHz And LO Power of +13 dBm, UG-387/U Flange, W Band



UNLESS OTHERWISE SPECIFIED:
DIMENSIONS ARE IN: inches
TOLERANCES ARE: [mm]
.XX ± .01 [±.25]
.XX ± .001 [±.025]

* THESE DIMENSIONS AND TOLERANCES
SUPERSEDE NOTE #1 ON TITLE BLOCK.

PE PASTERNAK®
THE ENGINEER'S RF SOURCE

Pasternack Enterprises, Inc.
P.O. Box 16759 | Irvine | CA | 92623
Phone: (949) 261-1920 | Fax: (949) 261-7451
Website: www.pasternack.com | E-Mail: sales@pasternack.com

DWG TITLE

PE13U1000

FSCM NO. 53919

NOTES:
1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES [mm].

CAD FILE 072015

SCALE N/A

SIZE A

2233