



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5029-001

500 - 1000 MHz
500 WATTS

Solid State Broadband High Power RF Amplifier

The 5029-001 is a 500 Watt broadband amplifier that covers the 500 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5029-001 comes with an extended



	<u>Parameter</u>	<u>Specification @ 25° C</u>
<u>Electrical</u>		
1	Frequency Range	500 – 1000 MHz
2	Saturated Output Power	500 Watts typical
3	Power Output @ 1dB Comp.	300 Watts min
4	Small Signal Gain	+58 dB min
5	Gain Flatness	± 2.0 dB
6	IP ₃	+61 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 300 Watts
9	Spurious Signals	> -60 dBc typical @ 300 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	6000 Watts max
12	AC Input	186 – 264 VAC, single phase
13	RF Input	0 dB max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
<u>Mechanical</u>		
16	Dimensions	31" x 24" x 26"
17	Weight	360 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

ORDERING MODELS

- ◇ R - Rear Panel Connectors
- ◇ F - Front Panel Connectors
- ◇ RE - Rear Panel Connectors and Control Option
- ◇ FE - Front Panel Connectors and Control Option