



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5900796
20 - 500 MHz
100 WATTS
LINEAR POWER RF AMPLIFIER

**Solid State
 Broadband High
 Power RF Amplifier**

The 5900796 is a 100 Watt broadband amplifier that covers the 20 – 500 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5900796 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	20 – 500 MHz
2	Saturated Output Power	100 Watts typical
3	Power Output @ 1dB Comp.	60 Watts min
4	Small Signal Gain	+52dB min
5	Gain Flatness	+/- 1.5dB max @ small signal +/- 1dB @ power
6	IP ₃	+54 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 60 Watts
9	Spurious Signals	> -60 dBc typical @ 60 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	12Amps max 2 Amp max @ blanked
12	DC Input	28 VDC nominal
13	RF Input	0 dBm max
14	Blanking - TTL	“High”: un-blanked “Low”: Blanked
15	Blanking Speed	100uS
Mechanical		
16	Dimensions	8.6” x 3.7” x 5.2”
17	Weight	4.2 Lbs.
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
Environmental		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000’ Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

