# **TGD-A2 SERIES**

# From Tiger Microwave **Dassive** Components

# **TGD-A2 SERIES**





## FEATURES AND APPLICATION:

TGD-A2 series 90° hybrid adopts strip line structure. It gets low insertion loss, high isolation, good amplitude and phase accuracy, high power handling and so on. Quality conformity can be guaranteed even under mass production. The series is Tiger's standard product and can be customized according to specific needs.

TGD-A2050 is mainly used to combine and split power in the fields of communication, EW, radar, measuring and testing and so on.


## **TECHNICAL SPECIFICATIONS:**

Frequency Range	Insertion Loss	Isolation	VSWR	Amplitude Balance
0.2-0.4GHz	0.30dB	22dB	1.20	$\pm 0.5 dB$
Phase Balance	Connector	Power Handling		
±2 °	SMA-F	50W		

## **ENVIRONMENTAL PARAMETERS:**

WORKING TEMPERATURE: -55~+85  $\ensuremath{\mathcal{C}}$ STORAGE TEMPERATURE: -55~+100 C

## OUTLINE: mm



## **TYPICAL PLOT:** Incortion loss

	1					
						1
						Г
0.0.000			 	 		
		_				1
			 			h
						Г
						1
			 			17
- A . H						



# Phase Balance

VSW R(input)

## VSWR(output)





## FEATURES AND APPLICATION:

TGD-A2 series 90° hybrid adopts strip line structure. It gets low insertion loss, high isolation, good amplitude and phase accuracy, high power handling and so on. Quality conformity can be guaranteed even under mass production. The series is Tiger's standard product and can be customized according to specific needs.


TGD-A2051 is mainly used to combine and split power in the fields of communication, EW, radar, measuring and testing and so on.

## **TECHNICAL SPECIFICATIONS:**

Frequency Range	Insertion Loss	Isolation	VSWR	Amplitude Balance
0.4-0.8GHz	0.30dB	22dB	1.20	$\pm 0.5 dB$
Phase Balance	Connector	Power Handling		
±2°	SMA-F	50W		


## **ENVIRONMENTAL PARAMETERS:**

WORKING TEMPERATURE: -55~+85°C STORAGE TEMPERATURE: -55~+100°C



## TYPICAL PLOT:

sertion	4.1	may 0. 5 0	97 R.K.I	 	_	
					<b>V</b> ( )	
					<b>W</b> 81	
-				 		



Phase Balanc	e	RTF - 90 .		¥2. ¥1. ¥2.	
- 40 - 400 - 400					700 MB2 -00 60a 800 MB2 000 MB2 000 MB2
				~	







Tiger Microwave Industrial Park, NO.18, Xinwen Road, Hi -Tech West Zone, Chengdu, China Tel: +86-28-62811638 Fax: +86-28-62811637 cdtiger@tiger-mw.com http://en.tiger-mw.com

Tiger Microwave Industrial Park, NO.18, Xinwen Road, Hi -Tech West Zone, Chengdu, China Tel: +86-28-62811638 Fax: +86-28-62811637 cdtiger@tiger-mw.com http://en.tiger-mw.com