




FTP-14BR

BIAS TAP



The FTP-14BR Bias Tap is used to provide a DC path to one side of a 50 Ohm transmission line. An integral blocking capacitor isolates the DC from the other side of the line.

Frequency Range	50 – 512 MHz
Insertion Loss	0.2 dB maximum
VSWR	1.3:1 maximum
RF Power	200 W CW
DC Resistance	1 Ohm maximum
DC Voltage	200 Volts maximum
DC Current	700 mA maximum