



ANATECH ELECTRONICS INC
RF & Microwave Filters & Products

136 MHz Highpass Filter

Part Number: AE136H9874



Electrical specifications

Cutoff Frequency: 136 MHz

Passband: 136-2000 MHz

Insertion loss: ≤ 1.0 dB

Return loss 1: ≥ 15 dB@136-1000 MHz

Return loss 2: ≥ 10 dB@1000-2000 MHz

Rejection: ≥ 50 dB@ ≤ 126 MHz

Power Handling: 50 Watts

Mechanical

Mounting Method: Threaded Mounting Holes

Connector Type: Type N Female

Dimensions: 3.82" x 2.00" x 1.50" in

Environmental

Operating Temperature: -45 to +85° C

Storage Temperature: -55 to +95° C

Shock: 20 G. 11ms

Vibration: 20 G. 5 to 200 MHz

Outline Drawing:

