



ANATECH ELECTRONICS, INC.

Manufacturer of RF & Microwave Filters and Products



70 MHz Bandpass Filter

Part Number: AE70B5132

Specifications:

Center Frequency: 70 MHz

Insertion Loss: <4dB

Return Loss Passband 66.5-73.5 MHz >14dB

Rejection >40dB @ 0-40 MHz

☐ >40dB @ 85-200 MHz

☐ >40dB @ 60 MHz

☐ >40dB @ 80MHz

☐ >75dB @ 47.5-52.5 MHz

Phase Ripple: <20deg 67.5-72.5 MHz/Z

Response Plot:

