



# ANATECH ELECTRONICS, INC.

Manufacturer of RF & Microwave Filters and Products



## 123.54 MHz Crystal Filter

Part Number: AM123.54CR206

|                            |                                  |
|----------------------------|----------------------------------|
| Filter Type                | Wide Band Xtal BP Filter         |
| Center Frequency (Fo)      | 123.54MHz                        |
| 3 dBc Band Width:          | ±300 KHz Min                     |
| Insertion Loss:            | 5 dB Max                         |
| Pass Band Ripple:          | 2 dB Typical                     |
| @ 3.3 MHz:                 | 50 dB Min                        |
| Spurious:                  | 30 dB Typical                    |
| Spurious Frequency Region: | +200KH to Approx. 3 MHz above Fo |
| Impedance:                 | 50Ohms                           |
| Workmanship                | IPC-610 Class 2                  |
| RoHs COMPLIANT             | NO                               |

**Mechanical Package Style: Thru hole size TBD**

