## **Approved Internet/Email Copy**

## BROADWAVE TECHNOLOGIES INC.

## MODEL 854 - 874 - MFB

## IMPEDANCE MATCHING PAD W/ DC BLOCK

Frequency Range: 1 - 1800 MHz

Impedance: 50 Ohms nominal (Male side)

75 Ohms nominal (Female side)

Insertion Loss: 5.7 dB nominal

VSWR: 1.50:1 maximum

Input Power: 1 Watt average

Connectors: BNC Male / Female

Outline Drawing: MED - 0103

ECF#	Date	Rev.
Issue	2/25/05	0

Approved By: \_\_\_\_\_