



ANATECH ELECTRONICS, INC.

Manufacturer of RF & Microwave Filters and Products



60 MHz Bandpass Filter

Part Number: AE60B5479

Specifications:

Center Frequency: 60 MHz

Insertion Loss @ Fc: <4dB

0.15dB @ 58.5 MHz

0.15dB @ 61.5 MHz

3dB @ 53.8 -54.2 MHz

3dB @ 65.8 -66.2 MHz

>40dB @ 50.47 MHz

>40dB @ 69.33 MHz

>40dB @ 0-20 MHz

>40dB @ 85-200 MHz

>68dB @ 77.42-79.92 MHz

>55dB @ 32 MHz

VSWR @ 56.5-63.5 MHz 1.5:1 (Return Loss >14dB)

Phase Ripple: <20 Deg. @ 56.5-63.5 MHz

Response Plot:

