

50 Ohm N Male To 75 Ohm N Female Matching Pad Operating From DC to 2 GHz RoHS Compliant



TECHNICAL DATA SHEET

PE7027

Configuration	
Design	Fixed Matching Pad
Body Style	Straight
Connector 1	N Male
Impedance 1	50 Ohms
Connector 2	N Female
Impedance 2	75 Ohms
Electrical Specifications	
Frequency Range, GHz	DC to 2
Maximum VSWR	1.2:1
Maximum Attenuation, dB	5.7
Attenuation Accuracy	± 0.5
Maximum Input Power, Watts	1
Directionality	Bidirectional
lechanical Specifications	
Temperature	
Operating Range,deg C	-30 to +70
Size	
Length, in [mm]	2.24 [56.9]
Width/Dia., in [mm]	0.83 [21.08]
Body Material and Plating	Brass, Nickel
Connector 1	
Туре	N Male
Inner Conductor Material and Plating	Brass, Gold
Coupling Nut Material and Plating	Brass, Nickel
Body Material and Plating	Brass, Nickel
Connector 2	
Туре	N Female
Inner Conductor Material and Plating	Beryllium Copper, Gold
Body Material and Plating	Brass, Nickel
compliance Certifications (visit www.Pasternack.	
RoHS Compliant	Yes

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com

Compliant PE7027







50 Ohm N Male To 75 Ohm N Female Matching Pad Operating From DC to 2 GHz RoHS Compliant

TECHNICAL DATA SHEET

Plotted and Other Data Notes:

Values at 25 °C, sea level 75 Ohm Type N Connectors Mate Only With Other 75 Ohm Connectors. Mating With 50 Ohm Connectors May Damage Center Conductors.

50 Ohm N Male To 75 Ohm N Female Matching Pad Operating From DC to 2 GHz RoHS Compliant from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 50 Ohm N Male To 75 Ohm N Female Matching Pad Operating From DC to 2 GHz RoHS Compliant PE7027

URL: http://www.pasternack.com/50-ohm-n-male-75-ohm-n-female-matching-pad-pe7027-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

PF7027 RFV

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451 Sales@Pasternack.com · Techsupport@Pasternack.com





PE7027



PE7027 CAD Drawing

50 Ohm N Male To 75 Ohm N Female Matching Pad Operating From DC to 2 GHz RoHS Compliant

