



70 MHz Bandpass Filter

Part Number: AE70B6000

Specifications:

Center Frequency: 70 MHz

Insertion Loss < 4 dB

Passband 65-75 MHz <0.5dB Flatness

Passband 65-75 MHz >14dB

Rejection: >40dB @ 0-40 MHz

>75dB @ 45-55 MHz

>40dB @ 60 MHz

>40dB @ 85-200 MHz

Passband 65-75 Ph Lin <40 deg

Response Plot:

