




UHF SATCOM BANDPASS FILTER

FBV-215A



PASSBAND INSERTION LOSS, 291 to 318.3 MHz:	1.0 dB max.
PASSBAND VSWR, 292 to 318 MHz:	1.4:1 max.
REJECTION: 0 to 270 MHz:	100 dB min.
340 to 1,000 MHz:	90 dB min.
RF POWER, 291 to 318.3 MHz:	400 W CW
CONNECTORS:	Type N-female
WEIGHT:	5 lbs., 10 oz.