



ANATECH ELECTRONICS, INC.

Manufacturer of RF & Microwave Filters and Products



56.98 MHz Bandpass Filter

Part Number: AE56B3995

Specifications:

Center Frequency: 56.98 MHz

Insertion Loss <4dB

55.48-58.48 MHz Flatness <0.15dB

3dB pt 50.78-51.18 MHz

3dB pt 62.78-63.18 MHz

Return Loss @53.48-60.48 >14dB

Rejection >40dB @ 0-20MHz

☐ >40dB @ 85-200 MHz

☐ >40dB @ 46.62 & 67.34 MHz

☐ >75dB @ 76.4-78.95 MHz

☐ >55dB @ 35 MHz

Phase Ripple <20deg 54.48-59.48 MHz

☐

Response Plot:

